

# SMART 7130 i3 1215U

**CPU:** Intel Alder Lake Core i3 12th Gen 1215U Processor  
Max up to 4.40GHz, 6 Core 8 Threads, Cache 12 MB  
Intel® UHD Graphics



## PRODUCT HIGHLIGHT

- A full-featured Micro Computer PC
- Support 2 x DDR4 RAM slots, max 64GB DDR4 RAM
- 1x RJ45 LAN, 1x DP Port, 1x HDMI 1.4
- Power Switch with Blue LED light.

A micro PC, also known as a mini PC or compact PC, is a small-sized computer that offers functionality similar to a traditional desktop or laptop computer but in a smaller form factor. These PCs are designed to be space-efficient, energy-efficient, and often portable, making them suitable for various applications, including home entertainment, office work, digital signage, and embedded systems

### Basic Information :

|                    |  |
|--------------------|--|
| <b>CPU</b>         | Onboard Intel Core i3 12 <sup>th</sup> Gen Processor |
| <b>TDP</b>         | 15W  |
| <b>Motherboard</b> | BPAU05, 12L, black, Size: 107x107x1.6mm              |
| <b>Memory</b>      | 2x SO-DIMM DDR4 3200MHz                              |
| <b>OS Support</b>  | Windows 11 home/ Windows 11 pro/Linux                |
| <b>Audio</b>       | Intel High Definition Audio Controller               |
| <b>Network</b>     | 1x RJ45 Giga LAN 10M/100M/1000M                      |
| <b>Video</b>       | Intel UHD Graphics for 12th Gen Intel Processors     |

### Input / Output Port :

|               |   |
|---------------|---|
| <b>Switch</b> | 1x Power On/Off Switch with LED                     |
| <b>Power</b>  | 1x DC In, 5.5mm                                     |
| <b>USB</b>    | 4x USB 3.2 Gen2 (Type A)                            |
| <b>Type-C</b> | 1x Data only (Data + DP) & 1x PD+USB3.2 (Data + DP) |
| <b>HDMI</b>   | 1x HDMI 1.4 4K@30Hz                                 |
| <b>DP</b>     | 1x DP 1.4 8K@60Hz                                   |
| <b>LAN</b>    | 1x RJ45 Giga LAN 10M/100M/1000M                     |
| <b>Audio</b>  | 1x Audio 3.5mm Combo audio jack                     |

### Wi-Fi and Bluetooth

|                |                              |
|----------------|------------------------------|
| <b>Wi-Fi</b>   | M.2 2230 AC Wi-Fi or Wi-Fi 6 |
| <b>Antenna</b> | 2x Antenna Inbuilt           |

### Storage :

|             |  |
|-------------|--|
| <b>NVME</b> | 1x M.2 KEY-M Slots, 2280 Type, PCIe4.0*4 |
|-------------|--|

### Power and Working Environment :

|                        |  |
|------------------------|--|
| <b>Input</b>           | AC 100~240V, 50/60Hz, 19V/3.42A, 5.5*2.5mm |
| <b>Operating Temp.</b> | -5° ~ 40°, RH 10% ~ 90%                    |
| <b>Storage Temp.</b>   | 0° ~ 60°, RH 5% ~ 95%                      |

### Production Dimension & Details :

|                     |                            |
|---------------------|----------------------------|
| <b>Size</b>         | 112.6mm X 112.6mm X 36.5mm |
| <b>Weight</b>       | About 550g                 |
| <b>Shell</b>        | Plastic                    |
| <b>Cooling Mode</b> | With Fan                   |



## APURVA COMPUTERS TECHNOLOGIES PVT. LTD.

**Corporate Office:** 1210, 12th Floor, One World West, Bopal Approach BRTS Bus stop, Near Vakil Saheb Bridge, Bopal, Ahmedabad-380058 (Gujarat) India.

**Registered Office:** 2nd Floor, Manivir Complex, Vitthal Press Road, Surendranagar-363001 (Gujarat), India.

**Toll Free:** 8800 860 861 **Email:** sales@smartstation.in

**Website:** www.smartstation.in



Efficient • Transparent • Inclusive